

Serial Number: \_\_\_\_\_

Date: \_\_\_\_\_

Tech: \_\_\_\_\_

# LASER INTERFEROMETER GRAVITATIONAL WAVE OBSERVATORY

**-LIGO-**

**CALIFORNIA INSTITUTE OF TECHNOLOGY**

**MASSACHUSETTS INSTITUTE OF TECHNOLOGY**

Document Type	DCC Number	October 4, 2002
	T020031-C-C	
<b>Optical Lever PD Interface Board (Rev B) Test Plan</b>		
J. Heefner		

Distribution of this draft:  
This is an internal working note of the LIGO Laboratory

**California Institute of Technology**  
**LIGO Project – MS 18-33**  
**Pasadena, CA 91125**  
Phone (626) 395-2129  
Fax (626) 304-9834  
E-mail: info@ligo.caltech.edu

**Massachusetts Institute of Technology**  
**LIGO Project – MS 20B-145**  
**Cambridge, MA 01239**  
Phone (617) 253-4824  
Fax (617) 253-7014  
E-mail: info@ligo.mit.edu

www: <http://www.ligo.caltech.edu/>

Serial Number: \_\_\_\_\_

Date: \_\_\_\_\_

Tech: \_\_\_\_\_

## 1 Introduction

The tests described below are required to verify the correct operation of the Optical Lever PD Interface Board (D010033, Rev B). It is important to note that all board outputs and monitors on the P1 are differential and must be measured differentially.

## 2 Test Equipment

Dynamic Signal Analyzer  
Oscilloscope  
Power supplies

## 3 Tests

### 3.1 Input Power

Record the input voltage and current in the table below. Values should be +/-20mA of the nominal values.

Supply	Nominal Current	Actual	Pass/Fail
+15 V	0.25 A		
-15 V	0.25 A		

### 3.2 Filter Response

The nominal response of each channel is a 4<sup>th</sup> order 800Hz low pass filter. In addition to this filter, there are also whitening filters that can be selected. Each whitening section has zeros at 2Hz and 9.5KHz and poles at 40Hz and 500Hz. Each section will be tested separately by grounding the pin listed in the Filter Section/Enable column of the table. Using the dynamic signal analyzer, verify and record the response of each channel in the table below. Channels are considered to be responding correctly if the magnitude and phase are within 2dB and 5 degrees, respectively of the nominal values. A plot of the nominal response is shown on the last page of this document.

Channel/ Input	Output	Filter Section/ Enable	Gain/Phase at 2Hz Nom 3dB/ 41deg	Gain/Phase at 40Hz Nom 23dB/ 30deg	Gain/Phase at 1KHz Nom 8.7dB/ -277deg
SEG1-1/ J7-1, J7-2	J4-1, J4-2	1/ P1-17A			
SEG1-1/ J7-1, J7-2	J4-1, J4-2	2/ P1-18A			
SEG2-1/ J7-3, J7-4	J4-5, J4-6	1/ P1-19A			
SEG2-1/ J7-3, J7-4	J4-5, J4-6	2/ P1-20A			
SEG3-1/ J7-5, J7-6	J4-9, J4-10	1/ P1-21A			
SEG3-1/ J7-5, J7-6	J4-9, J4-10	2/ P1-22A			
SEG4-1/ J7-7, J7-8	J4-13, J4-14	1/ P1-23A			
SEG4-1/ J7-7, J7-8	J4-13, J4-14	2/ P1-24A			
SEG1-2/ J3-1, J3-2	J4-17, J4-18	1/ P1-25A			

Serial Number: \_\_\_\_\_

Date: \_\_\_\_\_

Tech: \_\_\_\_\_

Channel/ Input	Output	Filter Section/ Enable	Gain/Phase at 2Hz Nom 3dB/ 41deg	Gain/Phase at 40Hz Nom 23dB/ 30deg	Gain/Phase at 1KHz Nom 8.7dB/ -277deg
SEG1-2/ J3-1, J3-2	J4-17, J4-18	2/ P1-26A			
SEG2-2/ J3-3, J3-4	J4-21, J4-22	1/ P1-27A			
SEG2-2/ J3-3, J3-4	J4-21, J4-22	2/ P1-28A			
SEG3-2/ J3-5, J3-6	J4-25, J4-26	1/ P1-29A			
SEG3-2/ J3-5, J3-6	J4-25, J4-26	2/ P1-30A			
SEG4-2/ J3-7, J3-8	J4-29, J4-30	1/ P1-31A			
SEG4-2/ J3-7, J3-8	J4-29, J4-30	2/ P1-32A			

### 3.3 Input to Output Connections

This test will confirm the connection from the inputs to the various board outputs. For this test a 100Hz, 1Vp-p sine wave is used. A channel is considered acceptable if the measured output sine wave has a 1Vp-p amplitude (+/-50mV) and the phase shown in the table below. All unused inputs should be grounded during this test.

Channel/ Input	EPICS Monitor P1-1A,C Volts 0deg?	QPD X EPICS P1-5A,C Volts 0deg?	QPD Y EPICS P1-6A,C Volts 0deg?	QPD Sum EPICS P1-7A,C Volts 180deg?
QPD1-1/ J7-1,2				
Channel/ Input	EPICS Monitor P1-2A,C Volts 0deg?	QPD X EPICS P1-5A,C Volts 0deg?	QPD Y EPICS P1-6A,C Volts 180deg?	QPD Sum EPICS P1-7A,C Volts 180deg?
QPD1-2/ J7-3,4				
Channel/ Input	EPICS Monitor P1-3A,C Volts 0deg?	QPD X EPICS P1-5A,C Volts 180deg?	QPD Y EPICS P1-6A,C Volts 180deg?	QPD Sum EPICS P1-7A,C Volts 180deg?
QPD1-3/ J7-5,6				
Channel/ Input	EPICS Monitor P1-4A,C Volts 0deg?	QPD X EPICS P1-5A,C Volts 180deg?	QPD Y EPICS P1-6A,C Volts 0deg?	QPD Sum EPICS P1-7A,C Volts 180deg?
QPD1-4/ J7-7,8				

Serial Number: \_\_\_\_\_

Date: \_\_\_\_\_

Tech: \_\_\_\_\_

<b>Channel/ Input</b>	<b>EPICS Monitor P1-8A,C Volts 0deg?</b>	<b>QPD X EPICS P1-12A,C Volts 0deg?</b>	<b>QPD Y EPICS P1-13A,C Volts 0deg?</b>	<b>QPD Sum EPICS P1-14A,C Volts 180deg?</b>
SEG1-2/ J3-1,2				
<b>Channel/ Input</b>	<b>EPICS Monitor P1-9A,C Volts 0deg?</b>	<b>QPD X EPICS P1-12A,C Volts 0deg?</b>	<b>QPD Y EPICS P1-13A,C Volts 180deg?</b>	<b>QPD Sum EPICS P1-14A,C Volts 180deg?</b>
SEG2-2/ J3-3,4				
<b>Channel/ Input</b>	<b>EPICS Monitor P1-10A,C Volts 0deg?</b>	<b>QPD X EPICS P1-12A,C Volts 180deg?</b>	<b>QPD Y EPICS P1-13A,C Volts 180deg?</b>	<b>QPD Sum EPICS P1-14A,C Volts 180deg?</b>
SEG3-2/ J3-5,6				
<b>Channel/ Input</b>	<b>EPICS Monitor P1-11A,C Volts 0deg?</b>	<b>QPD X EPICS P1-12A,C Volts 180deg?</b>	<b>QPD Y EPICS P1-13A,C Volts 0deg?</b>	<b>QPD Sum EPICS P1-14A,C Volts 180deg?</b>
SEG4-2/ J3-7,8				