



LASER INTERFEROMETER GRAVITATIONAL WAVE OBSERVATORY

LIGO Laboratory / LIGO Scientific Collaboration

LIGO-T1600605-v10

Advanced LIGO

September 22, 2023

Monitor Photodiodes for SQZ

Rich Abbott, Lisa Barsotti, Daniel Sigg

Distribution of this document:
LIGO Scientific Collaboration

This is an internal working note
of the LIGO Laboratory.

California Institute of Technology
LIGO Project – MS 18-34
1200 E. California Blvd.
Pasadena, CA 91125
Phone (626) 395-2129
Fax (626) 304-9834
E-mail: info@ligo.caltech.edu

Massachusetts Institute of Technology
LIGO Project – NW22-295
185 Albany St
Cambridge, MA 02139
Phone (617) 253-4824
Fax (617) 253-7014
E-mail: info@ligo.mit.edu

LIGO Hanford Observatory
P.O. Box 159
Richland WA 99352
Phone 509-372-8106
Fax 509-372-8137

LIGO Livingston Observatory
P.O. Box 940
Livingston, LA 70754
Phone 225-686-3100
Fax 225-686-7189

<http://www.ligo.caltech.edu/>

List of RF Photodiodes

Name	Location	Type	RF Chain	Comment
Newport 1611FS-AC:		Commercial		
FIBR_MIXER	SQZT0/FSS	1611	TTFSS	Laser/fiber locking PD
Broadband Photodetectors:		E1200428		
SHG_TRANS_RF35	SQZT0/SHG	BBPD	2ch demod	SHG locking (IR)
OPO_REFL_RF80	SQZT7/OPO	BBPD	2ch demod	OPO locking (GR)
LSC RF Photodetectors:		E1400099		
CLF_REFL_RF6	SQZT7/CLF	ALIGO	2ch demod	CLF phase. locking
FC_REFL_RF40	SQZT7/FC	ALIGO	2ch demod	FC locking
		D980454		
PMC_REFL_RF24	SQZT0/PMC	iLIGO	2ch demod	PMC locking
Existing OMC DCPD:		E1300521		
OMC_TRANS_RF3	In-vac	ALIGO	2ch demod	Squeeze angle locking
Thorlabs PDA100A:		Commercial		
FC_BEAT_RF1	SQZT7/FC	PDA100A	Fast ADC	FC beat note
Homodyne Photodetector:		E1700135		
HD_DIFF_RF3	SQZT7/HD	ALIGO	2ch demod	LO locking/diagnostics

List of Quad Detectors

Name	Location	Type	Chain	Comment
New 105 kHz Quads:		E2000502		
RLF_REFL_A	In-vac	ALIGO	RLF	FC locking/alignment
RLF_REFL_B	In-vac	ALIGO	RLF	FC locking/alignment
Green Quad:		TBD		
FC_TRANS_A	SQZT8/green	ALIGO	QPD	FC alignment
FC_TRANS_B	SQZT8/green	ALIGO	QPD	FC alignment

List of DC monitor photodiodes

Name	Location	Type	S	F	W	Comment
4-chn Generic PD interface (SQZT0):						
PMC_TRANS_DC/LF	SQZT0/FSS	PDA100A	×	×	×	DC of laser/fiber locking PD
SHG_TRANS_DC/LF	SQZT0/SHG	BBPD	×	×	×	DC of SHG locking (IR)
LASER_IR_DC/LF	SQZT0/PD1	PDA100A	×	×	×	Power of SQZ laser
SHG_GR_DC/LF	SQZT0/PD2	PDA100A	×	×	×	SHG green power (GR)
4-chn Generic PD interface (SQZT7):						
CLF_TRIG_DC	SQZT7/PD3	PDA100A	×	×		Trigger PD CLF path
OPO_IR_PD_LF	SQZT7/IR	PDA100A	×	×		DC of OPO transmitted (IR)
CLF_REFL_DC	SQZT7/CLF	ALIGO	×			DC of CLF refl. locking
OPO_REFL_DC	SQZT7/OPO	BBPD	×			DC of OPO refl. locking (GR)
4-chn Generic PD interface (SQZT8):						
FC_TRANS_C	SQZT8/GR	PDA100A	×	×		FC green transmitted light
FC_TRANS_D	SQZT8/IR	Femto	×	×		FC red transmitted light
DC Outputs of LSC RF PD interface:						
FIBR_PD_DC/LF	SQZT0/FSS	1611	×	×		DC of laser/fiber locking PD
PMC_REFL_DC/LF	SQZT0/PMC	iLIGO	×	×		DC of PMC locking PD
CLF_REFL_LF	SQZT7/CLF	ALIGO		×	+	DC of CLF refl. locking
OPO_REFL_LF	SQZT7/OPO	BBPD		×	+	DC of OPO refl. locking (GR)
FC_REFL_LF	SQZT7/FC	ALIGO		×	+	DC of FC refl. locking (GR)
FC_BEAT_LF	SQZT7/FC	PDA100A		×	+	DC of FC/OPO beat note (GR)
Homodyne interface:						
HD_B_DC	SQZT7/HD	ALIGO		×	+	PD B of homodyne
HD_DIFF_DC	SQZT7/HD	ALIGO		×	+	Difference of homodyne PDs
HD_A_DC	SQZT7/HD	ALIGO		×	+	PD A of homodyne
Unamplified DC Monitors:						
SHG_FIBR_REJECTED_DC	In-vac	PD	×			Rejected pump power
CLF_FIBR_REJECTED_DC	In-vac	PD	×			Rejected CLF power

FC_FIBR_REJECTED_DC	In-vac	PD	×			Rejected green FC power
OFI_A_REJECTED_DC	In-vac	PD	×			OFI monitor HAM7
OFI_B_REJECTED_DC	In-vac	PD	×			OFI monitor HAM5
FIBR_TRANS_DC/LF	SQZT0/DC1	SM1PD1A	×	×	×	Transmitted by laser fiber
FIBR_LASER_DC	SQZT0/DC2	SM1PD1A	×			Squeezer laser fiber
CLF_LAUNCH_DC	SQZT0/DC4	SM1PD1A	×			Injected into CLF fiber
CLF_REJECTED_DC	SQZT0/DC3	SM1PD1A	×			Rejected before injection
SHG_LAUNCH_DC	SQZT0/DC7	SM1PD1A	×			Injected into pump fiber
SHG_REJECTED_DC	SQZT0/DC6	SM1PD1A	×			Rejected before injection
SEED_LAUNCH_DC	SQZT0/DC5	SM1PD1A	×			Seed beam injection
LO_LAUNCH_DC	SQZT0/DC8	SM1PD1A	×			LO beam injection
FC_FIBR_LAUNCH_DC	SQZT0/DC11	SM1PD1A	×			Injected into FC green fiber
OPO_REFL_REJECTED_DC	SQZT7/DC9	SM1PD1A	×	×	×	Rejected OPO refl. power
OPO_TRANS_DC/LF	SQZT7/DC10	PDA100A	×	×	×	Trans. green OPO power (GR)
FC_REFL_REJECTED_DC	SQZT7/DC12	SM1PD1A	×	×	×	Reject. FC REFL power (GR)
FC_BEAT_REJECTED_DC	SQZT7/DC13	SM1PD1A	×			Reject. FC BEAT power (GR)
SPARE_A_DC	TBD	TBD	×			Spare (SQZT0)
SPARE_B_DC	TBD	TBD	×			Spare (SQZT7)
SPARE_C_DC	TBD	TBD	×			Spare (SQZT8)
SPARE_D_DC	TBD	TBD	×			Spare (SQZT8)
Trigger PD:						
SYS-MOTION_C_SHUTTER_H_TRIGGER	SQZT7/PD3	PDA100A	×			Trigger PD CLF path

S: Slow controls readback; F: Fast DAQ readback; W: Whitened readback (×: standard whitening, +: custom whitening)